

ATS-US

GROWATT (ATS-US) Auto Transfer Switch and US Split Phase Transformer

- ATS-US comes with built-in transformer
- ATS 5000T -US has a maximum sum of L1-N and L2-N simultaneous output is 5000VA
- ATS 11400T -US has a maximum sum of L1-N and L2-N simultaneous output is 11400VA
- Maximum continuous power is 5.0kw for energy storage



P O W E R
- I N G O
T O M O -
R R O W O

Growatt powering tomorrow

www.growatt-america.com

Product model	ATS 5000T- US	ATS 11400T-US
Input Data		
EPS		
Normal Voltage	240/208V	
Normal Frequency	50/60Hz	
Max. Power	5000VA	11400VA
Max. Current	21A@240Vac/24A@208Vac	48A@240Vac/55A@208Vac
AC Grid		
Normal Voltage	240/208V	
Normal Frequency	50/60Hz	
Max. Power	5000VA	11400VA
Max. Current	21A@240Vac/24A@208Vac	48A@240Vac/55A@208Vac
Output Data		
Split Phase Data		
Rated Power(L-L)	5000VA	11400VA
Rated power(L-N)	5000VA	
Output voltage	120/240Vac_104/208Vac	
Max continued current(L-N)	42A@240Vac/48A@208Vac	42A@240Vac/48A@208Vac
Max continued current(L-L)	21A@240Vac/24A@208Vac	48A@240Vac/55A@208Vac
General Data		
Cooling	Natural Convection	
Ingress Protection	NEMA 4X(IP65)	
Installation	Wall Mountable	
Operating Temperature Range	-25 ~ +55°C(-13 ~ +131°F)	
Weight	33lbs/15kg	
Dimensions (W/H/D)	18.9/10.8/4.1in(480/275/105mm)	
Warranty	10 Years	
UL1741:2018 CSA C22.2 NO 107.1:2016		

GROWATT USA INC. Address: 9227 Reseda Blvd. #435 Northridge, CA 91324. Sales Hotline : 818 800 9455 Service Hotline : 818 800 9177
Email: usa@ginverter.com